

Worksheet: Speedup

Array Sum Speedup

- Assume $T(S,P) = \text{WORK}(G,S)/P + \text{CPL}(G,S) = (S-1)/P + \log_2(S)$ for the parallel array sum computation shown in slide 4 (using the upper bound)
- Assume $S = 1024 \implies \log_2(S) = 10$
- Compute for 10, 100, 1000 processors (round to 1 decimal place)
 $T(S,P) = (S-1)/P + \log_2(S) = 1023/P + 10$
Speedup(10) = $T(1)/T(10) =$
Speedup(100) = $T(1)/T(100) =$
Speedup(1000) = $T(1)/T(1000) =$
- Why does the speedup not increase linearly in proportion to the number of processors?



Worksheet solution

- Estimate $T(S,P) \sim \text{WORK}(G,S)/P + \text{CPL}(G,S) = (S-1)/P + \log_2(S)$ for the parallel array sum computation shown in slide 4.
- Assume $S = 1024 \implies \log_2(S) = 10$
- Compute for 10, 100, 1000 processors
 - $T(P) = 1023/P + 10$, when $P > 1$
 - $\text{Speedup}(10) = T(1)/T(10) = 1023/112.3 \sim 9.1$
 - $\text{Speedup}(100) = T(1)/T(100) = 1023/20.2 \sim 50.6$
 - $\text{Speedup}(1000) = T(1)/T(1000) = 1023/11.0 \sim 93.7$
- Why does the speedup not increase linearly in proportion to the number of processors?
 - Because of the critical path length, $\log_2(S)$, is a bottleneck



Speedup Chart (linear scale)

