

ZOOM H4N: THE QUICK GUIDE



WAYS TO RECORD:

- BUILT IN MICROPHONES (STEREO)
- BUILT IN MICROPHONES + EXTERNAL MICROPHONES (4CH)
- AS AUDIO INTERFACE USING EITHER *STEREO* OR *4CH*
(RECORD DIRECTLY TO COMPUTER USING A PROGRAM SUCH AS **GARAGEBAND** OR **AUDACITY**)

TO RECORD:

- PRESS [REC] ONCE
- WHEN THE RED LIGHT IS FLASHING YOU WILL BE ABLE TO ADJUST RECORDING LEVEL WITHOUT ACTUALLY RECORDING
- WHEN READY, PRESS [REC] AGAIN TO BEGIN RECORDING
- USE THE [PLAY/PAUSE] BUTTON TO PAUSE OR RESUME RECORDING
- WHEN FINISHED, PRESS THE [STOP] RECORDING (THIS WILL FINISH AND SAVE THE RECORDING)



TO SWITCH BETWEEN RECORD MODES:

- PRESS THE [MENU KEY]
- USE THE [JOG DIAL] TO SCROLL TO *MODE*
(PRESS JOG DIAL TO SELECT)
- *ADJUST THE LEVEL OF BUILT IN MICROPHONES AND EXTERNAL MICROPHONES SEPERATELY BY SELECTING [MIC] OR [1]/[2] BEFORE PRESSING [+] OR [-] ON THE [REC LEVEL] BUTTON



TO USE AS AUDIO INTERFACE:

- PLUG USB CABLE INTO ZOOM AND COMPUTER
- USING THE [JOG DIAL], SELECT *AUDIO I/F*
- SELECT *CONNECT*
- SELECT *ZOOM H4N* AS THE INPUT DEVICE IN THE *PREFERANCES* OF YOUR AUDIO RECORDING SOFTWARE